

1210 Keramik Chip Kondensatoren



Selection Chart: 1210, COG Class 1 (+/- 30ppm/°C) RoHS COMPLIANT
 Capacitance Range Chart

Cap pF	Size	Tol	2000V	1500V	1000V	630V	500V	250V
10	1210	5						
22	1210	5						
47	1210	5	1210N470J202NT					
82	1210	5	1210N820J202NT					
100	1210	5	1210N101J202NT		1210N101J102NT	1210N101J631NT		
150	1210	5	1210N151J202NT		1210N151J102NT	1210N151J631NT		
220	1210	5	1210N221J202NT		1210N221J102NT	1210N221J631NT		
330	1210	5	1210N331J202NT		1210N331J102NT	1210N331J631NT		
390	1210	5	1210N391J202NT		1210N391J102NT	1210N391J631NT		
470	1210	5	1210N471J202NT	1210N471J152NT	1210N471J102NT	1210N471J631NT		
560	1210	5	1210N561J202NT	1210N561J152NT	1210N561J102NT	1210N561J631NT		
680	1210	5	1210N681J202NT	1210N681J152NT	1210N681J102NT	1210N681J631NT		
820	1210	5	1210N821J202NT	1210N821J152NT	1210N821J102NT	1210N821J631NT		
1000	1210	5		1210N102J152NT	1210N102J102NT	1210N102J631NT	1210N102J501NT	1210N102J251NT
1200	1210	5		1210N122J152NT	1210N122J102NT	1210N122J631NT	1210N122J501NT	1210N122J251NT
1500	1210	5			1210N152J102NT	1210N152J631NT	1210N152J501NT	1210N152J251NT
1800	1210	5			1210N182J102NT	1210N182J631NT	1210N182J501NT	1210N182J251NT
2200	1210	5			1210N222J102NT	1210N222J631NT	1210N222J501NT	1210N222J251NT
2700	1210	5				1210N272J631NT	1210N272J501NT	1210N272J251NT
3300	1210	5				1210N332J631NT	1210N332J501NT	1210N332J251NT
4700	1210	5					1210N472J501NT	1210N472J251NT 8.2nF max

Selection Chart: 1210, X7R Class 2 (+/- 15%) RoHS COMPLIANT
 Capacitance Range

Cap pF	Size	Tol	2000V	1500V	1000V	630V	500V	250V
120	1210	10	1210B121K202NT					
220	1210	10	1210B221K202NT					
330	1210	10	1210B331K202NT					
470	1210	10	1210B471K202NT	1210B471K152NT				
1000	1210	10	1210B102K202NT	1210B102K152NT	1210B102K102NT	1210B102K631NT		
1500	1210	10	1210B152K202NT	1210B152K152NT	1210B152K102NT	1210B152K631NT		
2200	1210	10	1210B222K202NT	1210B222K152NT	1210B222K102NT	1210B222K631NT		
2700	1210	10		1210B272K152NT	1210B272K102NT	1210B272K631NT		
3300	1210	10		1210B332K152NT	1210B332K102NT	1210B332K631NT		
4700	1210	10		1210B472K152NT	1210B472K102NT	1210B472K631NT		
5600	1210	10			1210B562K102NT	1210B562K631NT		
6800	1210	10			1210B682K102NT	1210B682K631NT		
8200	1210	10			1210B822K102NT	1210B822K631NT		
10nF	1210	10			1210B103K102NT	1210B103K631NT	1210B103K501NT	1210B103K251NT
15nF	1210	10			1210B153K102NT	1210B153K631NT	1210B153K501NT	1210B153K251NT
22nF	1210	10				1210B223K631NT	1210B223K501NT	1210B223K251NT
33nF	1210	10				1210B333K631NT	1210B333K501NT	1210B333K251NT
47nF	1210	10				39nF max	1210B473K501NT	1210B473K251NT
56nF	1210	10					1210B563K501NT	1210B563K251NT
120nF	1210	10						1210B124K251NT

BREDEMEIER ELECTRONICS GMBH TEL. +49 (89) 90 80 24 Fax +49 (89) 9437 9546

info@bredemeiergmbh.de www.bredemeiergmbh.de